

FIRE ALARM CONTROL PANEL



5~15zone



20~30zone



35~60zone

Type	Conventional type	Spare Battery	24VDC
Model	FMS-P5-5L...FMS-P5-100L	End of Line Resistance	10KΩ
Zone	5-100+	Max.Amount of smoke detectors	20 pcs/Loop
Input Voltage	220VAC/50Hz	Alarm Verifying Time	7seconds
Operation Voltage	24VDC	Exterior Resistance	Round-trip under 56Ω

5~15zone	20~30zone	35~60zone	65~90zone	95~100zone
300(W) 410(H) 107(D) mm	370(W) 510(H) 150(D) mm	480(W) 720(H) 200(D) mm	480(W) 850(H) 200(D) mm	480(W) 1000(H) 220(D) mm



FIRE ALARM CONTROL PANEL

FMS-P5-5L

The panel system is microcomputer designed for fire alarm, smoke exhaust, water sprinkle, fire-fighting foam control. All PCB are maintain. Auto test function makes it easy to check and control.



Function

1. **Alarm Verification** Double check the fire alarm signal to avoid false alarm.
2. **Battery self-protect** Battery is running lower 18VDC, it will stop discharging.
3. **Indication LED** Different color light to indicate different condition.
4. **Loop auto test and manual test** Test loop form 1 to the last automatically or set a certain loop manually to test.
5. **Annunciator Panel** is available.

