
## Fire Manual Call Point


# FMC-FP1


#### **Advantages**

- Auto-Return by pushing button, no need to disassemble the main body
- ♦Response light available to identify the operation completed
- ◆Reinforced transparent protective cover is reusable









### **Specifications**

Model	FMC-FP1
Voltage Range	24V DC
Alarm Current	30 mA
Alarm Current	24V DC 100mA
Sub-function	Phone jack; Confirmation / LED; Reset button
Option	Base
Material	Fire-Proof plastics
Dimensions	¢140(mm)
Weight	150g
Color	Red

#### **Order Information**

FMC-FP1 Fire Manual Call Point

